# BExBG21 Explosion Proof Xenon Beacon 21 Joule



The flameproof BExBG21 Xenon beacons are suitable for Zone 1, 2, 21 & 22 applications. Approved to IECEx, ATEX, Ex EAC and INMETRO standards.

The BExBG21 21 Joule beacons robust construction enables installation in the harshest of environments. The BExBG21 has three distinct user selectable flash patterns and for units with DC operating voltages a second stage flash pattern can be selected remotely. Additional features include a stainless steel guard and stainless steel mounting bracket as standard.

The BEx range features enclosures manufactured from corrosion proof, marine grade copper free LM6 aluminium with a chromate and powder coat finish. All models have two M20 cable entries, large termination areas containing in & out terminals and an ingress protection of IP66/67.

### Features

- Marine grade, corrosion proof, LM6 aluminium enclosure
- Xenon tubes mechanically secured against shock & vibration
- Dual Xenon flash tubes
- Glass lens & Stainless Steel guard
- Very large termination area.
- Dual M20 cable entries adaptors available.
- Stopping plug included.
- Ratchet adjustable stainless steel 'U' bracket.
- Reverse polarity diode fitted.
- IP66/67 ingress protection.
- 520 candela effective light intensity.
- UV stable PC, field replaceable, colour lens filter.

## **Approvals**

• IECEx KEM 10.0002 X

IEC 60079-0: 2011 IEC 60079-1: 2007-4 IEC 60079-31:2013

ATEX KEMA 00ATEX2 006X

EN 60079-0: 2012 + A11 EN 60079-1:2007 EN 60079-31: 2014

- TR-CU Ex EAC certificate: RU C-G B.AA71.B.00109
- Inmetro certificate: 10-IEx-0010

### Coding

- II 2G Ex d IIC T3 Gb Ta. -50°C to +70°C
- II 2D Ex tb IIIC T150°C Db Ta. -50°C to +40°C
- II 2D Ex tb IIIC T165°C Db Ta. -50°C to +55°C
- II 2D Ex tb IIIC T180°C Db Ta. -50°C to +70°C




















### **Specification**

•				
Energy:	21 Joules			
Flash rate:	1Hz, 2Hz & double strike 1Hz			
Peak Candela:	2,100,000 cd - calculated from energy (J)			
Effective Intensity cd:	1,050 cd - calculated from energy (J)			
Peak Candela:	118,537 cd* - measured ref. to I.E.S.			
Effective Intensity cd:	520 cd* - measured ref. to I.E.S.			
Lens colours:	Amber, Blue, Clear, Green, Magenta, Red & Yellow			
Voltages DC:	2 4vdc; 48vdc			
Voltages AC:	115vac; 230vac			
Ingress protection:	IP66/67			
Enclosure matl:	Marine grade copper free LM6 Aluminium			
Enclosure finish:	Chromate & powder coated finish - anti-corrosion.			
Colour:	RAL3000 Red (others available on request)			
Cable entries:	Dual M20 ISO (one stopping plug inc)			
Terminals:	0.5 - 2.5mm² (20-14 AWG)			
Enclosure volume:	<pre>&lt;2 litres</pre>			
Line monitoring:	Blocking diode included EOL Min. 500 Ohm 2w, or 3k3 Ohm 0.5w resistor or diode (DC versions) can be added			
Grounding stud:	M5			
Temperature range:	-50° to +70°C (-58°F to +158°F)			
Relative humidity:	90% at 20°C [68°F]			
Tube life:	Emissions are reduced to 70% after 8 million flashes			
Weight:	DC: 2.65kg/5.83lbs AC: 2.95kg/6.49lbs			
*All candela data is representative of performance with clear lens at optimum voltage.				

## **Part Codes**

<b>Version:</b> Product type:	Part cod	le: Explosion proof 21J Xenon Beacon		
Туре:	DP	Ex d, UV stable PC Colour Lens		
Voltage:	DC024 DC048 AC115 AC230	2 4V dc 48V dc 115V ac 2 40V ac		
Cable Entry Type: [e	JA B C D E F G	2 x M2 0x1.5mm 2 x 1/2" NPT - adaptors 2 x 3/4" NPT - adaptors 2 x M2 5x1.5mm - adaptors 1 x 1/2" NPT - adaptor 1 x 3/4" NPT - adaptor 1 x M2 5x1.5mm - adaptor M20 stopping plugs for unused entries supplied		
Adaptor/Stopping plug material: [m]	B N S	Brass Nickel Plated Stainless Steel		
Bracket/guard matl: [s]	1 2 3 4	A2 304 Stainless Steel A4 316 Stainless Steel A2 304 St/St with Equip. Tag A4 316 St/St with Equip. Tag (304)		
Product version: [v	] A1	Default - IECEx, ATEX, Ex EAC & INMETRO		
Enclosure colour: [x]	R S	Red RAL3000 Special - contact E2S		
Lens colour: [y]	A B	Amber C Clear M Magenta Y Yellow Blue G Green R Red		

# **Current Consumption**

Version:		Voltage:	Current:	
24V dc		20-28V dc	1.2A	
48V dc		42-54V dc	600mA	
115V ac	50/60Hz	+/-10%	560mA	
230V ac	50/60Hz	+/-10%	280mA	

### Flash Patterns

Pattern:	Туре:	Stg 2 (DC)
SF	1Hz (60fpm) Both Xenon tubes flash together	AF
AF	2 Hz (12 Ofpm) Xenon tubes flash alternately	SF
DF	1Hz (60fpm) Double strike flash	SF
		11 Ian 2017